

Analog or Digital Triple Output DC Power Supply



Adjustable 30V/3A

With fixed 5V and 12V outputs

Features:

- Triple Output: Adjustable 0-30V, 0-3A plus fixed 5V and 12V
- 0-30V Adjustable Voltage Output
- 0-3A Adjustable Current Output
- Independent 5V and 12V Outputs Provides Power for TTL or CMOS Projects
- Easy Snap Terminals for 5V and 12V outputs
- Overload and Short Circuit Protection
- Constant Voltage or Current
- Current Limiting Front Panel LED Indicator
- Binding Post Terminals for Variable Supply



Specifications

Voltage Output, DC	0 to 30 Volts
Current Output, DC	0 to 3 Amps
Ripple and Noise	<5mV
Line Regulation	<0.05%+10mV
Load Regulation	<0.05%+10mV
Fixed Output Voltage	5V/0.5A (cont.), 1A(max)
12V/0.5A (cont.), 1A(max)	
Display	Analog or Digital (V&A), 3 digit 0.1 res. LCD
Power	110/220VAC 50/60Hz
Dimensions	8 x 4.75 x 9" (203 x 121 x 229)
Weight	10.5lbs. (4.8Kg)

Ordering Information:

382203Analog DC Power Supply, 115/220 VAC
 382203-NISTAnalog DC Power Supply, 115/220 VAC with NIST.
 382213Digital DC Power Supply, 115/220 VAC
 382213-NISTDigital DC Power Supply, 115/220 VAC with NIST.

